

TD d'application de logique

Faire les regroupements nécessaires, puis donnez l'équation de chacune des variables ci-dessous. Plus le regroupement est important plus l'équation est ...

<p>A</p> <table border="1"> <thead> <tr> <th></th> <th>00</th> <th>01</th> <th>11</th> <th>10</th> </tr> </thead> <tbody> <tr> <td>00</td> <td>0</td> <td>0</td> <td>0</td> <td>0</td> </tr> <tr> <td>01</td> <td>0</td> <td>0</td> <td>0</td> <td>0</td> </tr> <tr> <td>cd 11</td> <td>0</td> <td>0</td> <td>1</td> <td>0</td> </tr> <tr> <td>10</td> <td>0</td> <td>0</td> <td>0</td> <td>0</td> </tr> </tbody> </table> <p>Equation de A :</p>		00	01	11	10	00	0	0	0	0	01	0	0	0	0	cd 11	0	0	1	0	10	0	0	0	0	<p>B</p> <table border="1"> <thead> <tr> <th></th> <th>00</th> <th>01</th> <th>11</th> <th>10</th> </tr> </thead> <tbody> <tr> <td>00</td> <td>0</td> <td>0</td> <td>0</td> <td>0</td> </tr> <tr> <td>01</td> <td>0</td> <td>0</td> <td>0</td> <td>0</td> </tr> <tr> <td>cd 11</td> <td>0</td> <td>0</td> <td>1</td> <td>1</td> </tr> <tr> <td>10</td> <td>0</td> <td>0</td> <td>0</td> <td>0</td> </tr> </tbody> </table> <p>Equation de B :</p>		00	01	11	10	00	0	0	0	0	01	0	0	0	0	cd 11	0	0	1	1	10	0	0	0	0	<p>C</p> <table border="1"> <thead> <tr> <th></th> <th>00</th> <th>01</th> <th>11</th> <th>10</th> </tr> </thead> <tbody> <tr> <td>00</td> <td>0</td> <td>0</td> <td>0</td> <td>0</td> </tr> <tr> <td>01</td> <td>0</td> <td>0</td> <td>0</td> <td>0</td> </tr> <tr> <td>cd 11</td> <td>0</td> <td>0</td> <td>1</td> <td>1</td> </tr> <tr> <td>10</td> <td>0</td> <td>0</td> <td>1</td> <td>1</td> </tr> </tbody> </table> <p>Equation de C :</p>		00	01	11	10	00	0	0	0	0	01	0	0	0	0	cd 11	0	0	1	1	10	0	0	1	1
	00	01	11	10																																																																									
00	0	0	0	0																																																																									
01	0	0	0	0																																																																									
cd 11	0	0	1	0																																																																									
10	0	0	0	0																																																																									
	00	01	11	10																																																																									
00	0	0	0	0																																																																									
01	0	0	0	0																																																																									
cd 11	0	0	1	1																																																																									
10	0	0	0	0																																																																									
	00	01	11	10																																																																									
00	0	0	0	0																																																																									
01	0	0	0	0																																																																									
cd 11	0	0	1	1																																																																									
10	0	0	1	1																																																																									
<p>D</p> <table border="1"> <thead> <tr> <th></th> <th>00</th> <th>01</th> <th>11</th> <th>10</th> </tr> </thead> <tbody> <tr> <td>00</td> <td>0</td> <td>0</td> <td>1</td> <td>1</td> </tr> <tr> <td>01</td> <td>0</td> <td>0</td> <td>1</td> <td>1</td> </tr> <tr> <td>cd 11</td> <td>0</td> <td>0</td> <td>1</td> <td>1</td> </tr> <tr> <td>10</td> <td>0</td> <td>0</td> <td>1</td> <td>1</td> </tr> </tbody> </table> <p>Equation de D :</p>		00	01	11	10	00	0	0	1	1	01	0	0	1	1	cd 11	0	0	1	1	10	0	0	1	1	<p>E</p> <table border="1"> <thead> <tr> <th></th> <th>00</th> <th>01</th> <th>11</th> <th>10</th> </tr> </thead> <tbody> <tr> <td>00</td> <td>0</td> <td>0</td> <td>0</td> <td>0</td> </tr> <tr> <td>01</td> <td>0</td> <td>0</td> <td>0</td> <td>0</td> </tr> <tr> <td>cd 11</td> <td>1</td> <td>1</td> <td>1</td> <td>1</td> </tr> <tr> <td>10</td> <td>1</td> <td>1</td> <td>1</td> <td>1</td> </tr> </tbody> </table> <p>Equation de E :</p>		00	01	11	10	00	0	0	0	0	01	0	0	0	0	cd 11	1	1	1	1	10	1	1	1	1	<p>F</p> <table border="1"> <thead> <tr> <th></th> <th>00</th> <th>01</th> <th>11</th> <th>10</th> </tr> </thead> <tbody> <tr> <td>00</td> <td>0</td> <td>0</td> <td>0</td> <td>0</td> </tr> <tr> <td>01</td> <td>1</td> <td>1</td> <td>1</td> <td>1</td> </tr> <tr> <td>cd 11</td> <td>1</td> <td>1</td> <td>1</td> <td>1</td> </tr> <tr> <td>10</td> <td>0</td> <td>0</td> <td>0</td> <td>0</td> </tr> </tbody> </table> <p>Equation de F :</p>		00	01	11	10	00	0	0	0	0	01	1	1	1	1	cd 11	1	1	1	1	10	0	0	0	0
	00	01	11	10																																																																									
00	0	0	1	1																																																																									
01	0	0	1	1																																																																									
cd 11	0	0	1	1																																																																									
10	0	0	1	1																																																																									
	00	01	11	10																																																																									
00	0	0	0	0																																																																									
01	0	0	0	0																																																																									
cd 11	1	1	1	1																																																																									
10	1	1	1	1																																																																									
	00	01	11	10																																																																									
00	0	0	0	0																																																																									
01	1	1	1	1																																																																									
cd 11	1	1	1	1																																																																									
10	0	0	0	0																																																																									
<p>G</p> <table border="1"> <thead> <tr> <th></th> <th>00</th> <th>01</th> <th>11</th> <th>10</th> </tr> </thead> <tbody> <tr> <td>00</td> <td>1</td> <td>1</td> <td>0</td> <td>0</td> </tr> <tr> <td>01</td> <td>1</td> <td>1</td> <td>0</td> <td>0</td> </tr> <tr> <td>cd 11</td> <td>0</td> <td>0</td> <td>1</td> <td>1</td> </tr> <tr> <td>10</td> <td>0</td> <td>0</td> <td>1</td> <td>1</td> </tr> </tbody> </table> <p>Equation de G :</p>		00	01	11	10	00	1	1	0	0	01	1	1	0	0	cd 11	0	0	1	1	10	0	0	1	1	<p>H</p> <table border="1"> <thead> <tr> <th></th> <th>00</th> <th>01</th> <th>11</th> <th>10</th> </tr> </thead> <tbody> <tr> <td>00</td> <td>1</td> <td>0</td> <td>0</td> <td>0</td> </tr> <tr> <td>01</td> <td>1</td> <td>0</td> <td>0</td> <td>0</td> </tr> <tr> <td>cd 11</td> <td>0</td> <td>0</td> <td>0</td> <td>1</td> </tr> <tr> <td>10</td> <td>0</td> <td>0</td> <td>0</td> <td>1</td> </tr> </tbody> </table> <p>Equation de H :</p>		00	01	11	10	00	1	0	0	0	01	1	0	0	0	cd 11	0	0	0	1	10	0	0	0	1	<p>I</p> <table border="1"> <thead> <tr> <th></th> <th>00</th> <th>01</th> <th>11</th> <th>10</th> </tr> </thead> <tbody> <tr> <td>00</td> <td>0</td> <td>0</td> <td>0</td> <td>0</td> </tr> <tr> <td>01</td> <td>1</td> <td>0</td> <td>0</td> <td>1</td> </tr> <tr> <td>cd 11</td> <td>1</td> <td>0</td> <td>0</td> <td>1</td> </tr> <tr> <td>10</td> <td>0</td> <td>0</td> <td>0</td> <td>0</td> </tr> </tbody> </table> <p>Equation de I :</p>		00	01	11	10	00	0	0	0	0	01	1	0	0	1	cd 11	1	0	0	1	10	0	0	0	0
	00	01	11	10																																																																									
00	1	1	0	0																																																																									
01	1	1	0	0																																																																									
cd 11	0	0	1	1																																																																									
10	0	0	1	1																																																																									
	00	01	11	10																																																																									
00	1	0	0	0																																																																									
01	1	0	0	0																																																																									
cd 11	0	0	0	1																																																																									
10	0	0	0	1																																																																									
	00	01	11	10																																																																									
00	0	0	0	0																																																																									
01	1	0	0	1																																																																									
cd 11	1	0	0	1																																																																									
10	0	0	0	0																																																																									
<p>J</p> <table border="1"> <thead> <tr> <th></th> <th>00</th> <th>01</th> <th>11</th> <th>10</th> </tr> </thead> <tbody> <tr> <td>00</td> <td>1</td> <td>0</td> <td>0</td> <td>1</td> </tr> <tr> <td>01</td> <td>0</td> <td>0</td> <td>0</td> <td>0</td> </tr> <tr> <td>cd 11</td> <td>1</td> <td>1</td> <td>1</td> <td>1</td> </tr> <tr> <td>10</td> <td>1</td> <td>0</td> <td>0</td> <td>1</td> </tr> </tbody> </table> <p>Equation de J :</p>		00	01	11	10	00	1	0	0	1	01	0	0	0	0	cd 11	1	1	1	1	10	1	0	0	1	<p>K</p> <table border="1"> <thead> <tr> <th></th> <th>00</th> <th>01</th> <th>11</th> <th>10</th> </tr> </thead> <tbody> <tr> <td>00</td> <td>1</td> <td>0</td> <td>0</td> <td>0</td> </tr> <tr> <td>01</td> <td>1</td> <td>1</td> <td>0</td> <td>0</td> </tr> <tr> <td>cd 11</td> <td>0</td> <td>1</td> <td>1</td> <td>0</td> </tr> <tr> <td>10</td> <td>0</td> <td>0</td> <td>1</td> <td>1</td> </tr> </tbody> </table> <p>Equation de K :</p>		00	01	11	10	00	1	0	0	0	01	1	1	0	0	cd 11	0	1	1	0	10	0	0	1	1	<p>L</p> <table border="1"> <thead> <tr> <th></th> <th>00</th> <th>01</th> <th>11</th> <th>10</th> </tr> </thead> <tbody> <tr> <td>00</td> <td>1</td> <td>0</td> <td>0</td> <td>0</td> </tr> <tr> <td>01</td> <td>0</td> <td>1</td> <td>1</td> <td>0</td> </tr> <tr> <td>cd 11</td> <td>1</td> <td>0</td> <td>0</td> <td>1</td> </tr> <tr> <td>10</td> <td>0</td> <td>0</td> <td>1</td> <td>0</td> </tr> </tbody> </table> <p>Equation de L :</p>		00	01	11	10	00	1	0	0	0	01	0	1	1	0	cd 11	1	0	0	1	10	0	0	1	0
	00	01	11	10																																																																									
00	1	0	0	1																																																																									
01	0	0	0	0																																																																									
cd 11	1	1	1	1																																																																									
10	1	0	0	1																																																																									
	00	01	11	10																																																																									
00	1	0	0	0																																																																									
01	1	1	0	0																																																																									
cd 11	0	1	1	0																																																																									
10	0	0	1	1																																																																									
	00	01	11	10																																																																									
00	1	0	0	0																																																																									
01	0	1	1	0																																																																									
cd 11	1	0	0	1																																																																									
10	0	0	1	0																																																																									